



SmartOnline 10kVA On-Line Double-Conversion UPS, 6U Rack/Tower, 200-240V, includes Bypass Switch

MODEL NUMBER: SU10000RT3U











Description

Tripp Lite SU10000RT3U 10,000VA / 10kVA / 9000 watt online, double-conversion UPS system offers complete power protection for critical network applications. This system delivers online, double-conversion UPS protection with zero transfer time, suitable for advanced networking applications. Fault-tolerant auto-bypass prevents unexpected service interruptions during UPS overload or internal fault conditions. Included detachable PDU with manual bypass switch enables hot-swappable replacement of entire UPS power module with no interruption to connected equipment. Enhanced availability, fault tolerance and simple hot-swap replacement options make this UPS ideal for advanced networking applications in data centers, computer rooms, network closets and rugged industrial locations.

Features

- Tripp Lite SU10000RT3U 10kVA / 10,000VA / 9000 watt on-line, double-conversion UPS system in 6U total rack/tower configuration (3U UPS power module and 3U external battery pack)
- Detachable PDU with manual bypass switch enables hot-swappable UPS power module replacement with no interruption in output power to connected networking equipment
- Fault tolerant electronic bypass maintains utility output during a variety of UPS fault conditions
- Hardwire input; 2 L6-30R and 4 L6-20R outlets
- Maximum installed rack depth of only 32.5 in. / 82.6cm
- Full-time active power conditioning provides clean, continuous dual-conversion AC output free of voltage fluctuations, power interruptions and line noise
- Double-conversion operation converts raw input from AC to DC, then resynthesizes output power back to perfect sine wave AC with enhanced protection from harmonic distortion, fast electrical impulses and other hard-to-solve power problems not addressed by other UPS types
- Maintains full-time sine wave output within 2% of selectable 200/208/220/230/240V nominal during brownouts as low 100V and overvoltages as high as 300V
- Supports 50/60Hz operation for worldwide frequency compatibility

Highlights

- 10kVA / 10,000VA / 9000W on-line double-conversion UPS;
 0.9 power factor
- 200/208/220/230/240V 50/60Hz
 output with economy mode option
- Included maintenance bypass switch enables live replacement of UPS with zero downtime
- 6U Rack / Tower compatible;
 Hot-swappable power and
 battery modules
- USB, RS232 & EPO ports; support for SNMP/WEB and contact-closure card options
- Front panel LEDs with detailed LCD monitoring and control screen
- Expandable runtime with optional external battery packs
- Hardwire input (3 wire); L6-30R & L6-20R outlets

Package Includes

- SU10000RT3UPM 3U UPS power module
- BP240V10RT3U external battery pack
- SUPDMB710 Detachable PDU with manual bypass switch
- Four post compatible rack rail kit (2 sets)
- Tower stands for upright tower configuration
- PowerAlert software, complete data cabling and user manual





- Expandable runtime is supported with optional BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH external battery packs
- Some external battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- · Highly efficient operation in optional economy mode significantly reduces BTU heat output and operating energy costs
- Battery independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even when batteries are expired and require replacement
- PowerAlert monitoring software offers detailed site power and UPS updates with support for safe auto-shutdown of connected systems as UPS batteries become depleted
- Includes Free PowerAlert monitoring software packages; PowerAlert LOCAL for desktops and small business networks, PowerAlert NSA (Network Shutdown Agent) for larger networks and PowerAlert NMS (Network Management System) for monitoring up to 250 SNMP-enabled UPS, PDU and other networking devices
- Supports detailed monitoring of equipment load levels, self-test data and utility power conditions via built-in RS-232 and USB interfaces
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- · Optional SNMPWEBCARD offers communications and control via secure remote web and network interfaces
- Optional RELAYIOCARD supports six configurable hard contact closure outputs for custom event notification
- Optional RELAYIOMINI interface module offers three configurable hard contact closure outputs for custom event notification (requires removal of USB interface module)
- Supports Emergency Power Off (EPO) via built-in interface
- Included rail kit supports 6U 19 inch rackmount installation in 4 post racks
- Optional 2POSTRMKITHD supports installation in 2 post 19 inch racks
- Front panel LEDs and LCD readout with scroll controls and password option supports visual monitoring of all major UPS functions and advanced UPS settings for charge level, nominal voltage selection, frequency conversion and other operational parameters
- LED / LCD display panel rotates for viewing in rackmount or tower configurations
- Network-grade AC surge and noise suppression
- Industrial mode option (factory preset) enables supports high current startup loads by momentarily switching to bypass mode in response to short duration overload conditions
- Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz (no de-rating)
- External battery packs are field replaceable and hot swappable

Specifications

| оитрит | | |
|--|--|--|
| Output Capacity Details | Supports up to 105% load continuously in double conversion mode, 106 to 125% for 1 minute, 126% to 150% for 30 seconds; Loads over 150% trigger immediate bypass mode operation to support loads directly from mains power; Double conversion mode is automatically restored as load levels are reduced to 95% or less | |
| Output Volt Amp Capacity (VA) | 10000 | |
| Output kVA Capacity (kVA) | 10 | |
| Output Watt Capacity (Watts) | 9000 | |
| Output kW Capacity (kW) | 9.0 | |
| Power Factor | 0.9 | |
| Nominal Output Voltage(s) Supported | 200V; 208V; 240V | |



| N : 137 # 5 () | |
|---|--|
| Nominal Voltage Details | Voltage selection via front panel LCD interface |
| Frequency Compatibility | 50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion |
| Frequency Compatibility Details | Output frequency matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz (no de-rating) |
| Output Voltage Regulation (Line Mode) | +/- 2% |
| Output Voltage Regulation (Economy Line Mode) | +/- 10% |
| Output Voltage Regulation (Battery Mode) | +/- 2% |
| UPS Output Receptacles | 4 L6-20R outlet(s); 2 L6-30R outlet(s) |
| Output Circuit Breakers | 20A double-pole (x2) protects 2 L6-20R outlets each, 30A double-pole (x2) protects 1 L6-30R outlet each |
| Output AC Waveform (AC Mode) | Pure Sine wave |
| Output AC Waveform (Battery Mode) | Pure Sine wave |
| INPUT | |
| Rated input current (Maximum Load) | 56.1A (200V), 54A (208V), 51A (220V), 48.8A (230V), 46.8A (240V) |
| Nominal Input Voltage(s) Supported | 200V AC; 208V AC; 240V AC |
| UPS Input Connection Type | Hardwire |
| UPS Input Connection Description | 3 wire single phase input (L1, L2, G) |
| Recommended Electrical Service | 60A |
| Input Phase | Single-Phase |
| | |
| BATTERY | |
| Full Load Runtime (min.) | 4.3 min. (9000w) |
| | 4.3 min. (9000w) 12.5 min. (4500w) |
| Full Load Runtime (min.) | |
| Full Load Runtime (min.) Half Load Runtime (min.) | 12.5 min. (4500w) |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime | 12.5 min. (4500w) Supports extended runtime with optional external battery packs |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime External Battery Pack Compatibility | 12.5 min. (4500w) Supports extended runtime with optional external battery packs BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime External Battery Pack Compatibility DC System Voltage (VDC) Battery Recharge Rate (Included | 12.5 min. (4500w) Supports extended runtime with optional external battery packs BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH 240 |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime External Battery Pack Compatibility DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) | 12.5 min. (4500w) Supports extended runtime with optional external battery packs BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH 240 Less than 8 hours from 10% to 90% (typical, full load discharge) |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime External Battery Pack Compatibility DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Replacement Description | 12.5 min. (4500w) Supports extended runtime with optional external battery packs BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH 240 Less than 8 hours from 10% to 90% (typical, full load discharge) |
| Full Load Runtime (min.) Half Load Runtime (min.) Expandable Battery Runtime External Battery Pack Compatibility DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Replacement Description | 12.5 min. (4500w) Supports extended runtime with optional external battery packs BP240V10RT3U; BP240V557C-1PH; BP240V787C-1PH; BP240V1037C-1PH; BP240V1407C-1PH 240 Less than 8 hours from 10% to 90% (typical, full load discharge) Hot-swappable, user replaceable external battery packs |





| LED Indicators | 6 LEDs indicate line power, online mode, economy/bypass mode, on-battery, charger and AC output status; LCD screen offers additional information and control options |
|---|---|
| Front Panel LCD Display | Selectable LCD display with scroll and selection buttons enables UPS control and detailed monitoring options; LED/LCD panel rotates for viewing in rack/tower formats; LCD Display supports ENGLISH, FRENCH, GERMAN, ITALIAN, SPANISH and PORTUGUESE (see manual) |
| Audible Alarm | Unique audible alarms for all major UPS, environmental and power conditions (see manual) |
| Alarm Cancel Operation | Alarm cancel switch |
| Switches | 2 Switches control off/on power status and alarm-cancel/self-test operation; 2 additional switches support set and execute scrolling LCD functions; bundled PDU includes bypass switch to enable hot-swap UPS power module replacement |
| SURGE / NOISE SUPPRESSION | |
| UPS AC Suppression Response Time | Instantaneous |
| EMI / RFI AC Noise Suppression | Yes |
| PHYSICAL | |
| Included Mounting Accessory Description | 2 sets of adjustable 4 post rack rails included; 2-9USTAND tower kit included |
| Installation Form Factors Supported with Optional Accessories | 2 post rackmount (2POSTRMKITHD) |
| Optional Mounting Accessory Notes | 2 sets of 2POSTRMKITHD required for 2 post rackmount installation of separate power module and battery pack |
| Primary Form Factor | Rackmount |
| UPS Power Module Dimensions (hwd, in.) | 5.14 x 17.5 x 25.82 |
| UPS Power Module Dimensions (hwd, cm) | 13.1 x 44.4 x 65.6 |
| Installed Whole System Maximum Rack Depth (in.) | 32.5 |
| Installed Whole System Maximum Rack Depth (cm) | 82.6 |
| Rack Height | 6U |
| UPS Power Module Weight (lbs.) | 43 |
| UPS Power Module Weight (kg) | 19.5 |
| Included Battery Pack Dimensions (hwd / in.) | 5.25 x 17.5 x 25 |
| Included Battery Pack Dimensions (hwd / cm) | 13.3 x 44.4 x 63.5 |
| Included Battery Pack Weight (lbs.) | 158.7 |
| Included Battery Pack Weight (kg) | 72 |
| UPS Shipping Dimensions (hwd / in.) | 27 x 42 x 45 |
| UPS Shipping Dimensions (hwd / cm) | 68.6 x 106.7 x 114.3 |





| Shipping Weight (lbs.) | |
|--|---|
| | 300 |
| Shipping Weight (kg) | 136.2 |
| Cooling Method | Fan |
| UPS Housing Material | Steel |
| ENVIRONMENTAL | |
| Operating Temperature Range | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius |
| Storage Temperature Range | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius |
| Relative Humidity | 0 to 95%, non-condensing |
| AC Mode BTU / Hr. (Full Load) | 3415 |
| AC Economy Mode BTU / Hr. (Full Load) | 1275 |
| AC Mode Efficiency Rating (100% Load) | 91% |
| AC Economy Mode Efficiency Rating (100% Load) | 96% |
| Operating Elevation (ft.) | 0-3000m (0 to 10,000 ft.) |
| Audible Noise | 60 dBA at front side 1 meter |
| Operating Elevation (m) | 0-3000 m |
| COMMUNICATIONS | |
| Communications Interface | USB (HID enabled); DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface |
| Network Monitoring Port Description | Additional contact closure support with optional RELAYIOCARD and RELAYIOMINI interface cards. RELAYIOMINI installation requires removal of panel containing USB ports |
| | |
| PowerAlert Software | Included |
| PowerAlert Software Communications Cable | USB, DB9 serial and EPO cables included |
| | |
| Communications Cable | USB, DB9 serial and EPO cables included |
| Communications Cable WatchDog Compatibility | USB, DB9 serial and EPO cables included |
| Communications Cable WatchDog Compatibility LINE / BATTERY TRANSFER | USB, DB9 serial and EPO cables included Supports Watchdog application, OS and hard-reboot restart options for remote applications |
| Communications Cable WatchDog Compatibility LINE / BATTERY TRANSFER Transfer Time | USB, DB9 serial and EPO cables included Supports Watchdog application, OS and hard-reboot restart options for remote applications No transfer time (0 ms.) in online, double-conversion mode |
| Communications Cable WatchDog Compatibility LINE / BATTERY TRANSFER Transfer Time Transfer Time (Economy Mode) Low Voltage Transfer to Battery | USB, DB9 serial and EPO cables included Supports Watchdog application, OS and hard-reboot restart options for remote applications No transfer time (0 ms.) in online, double-conversion mode 8 ms. typical power failure response in optional economy mode |
| Communications Cable WatchDog Compatibility LINE / BATTERY TRANSFER Transfer Time Transfer Time (Economy Mode) Low Voltage Transfer to Battery Power (Setpoint) High Voltage Transfer to Battery | USB, DB9 serial and EPO cables included Supports Watchdog application, OS and hard-reboot restart options for remote applications No transfer time (0 ms.) in online, double-conversion mode 8 ms. typical power failure response in optional economy mode 100V |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| Economy Mode Operation | Optional economy mode enables high efficiency bypass operation with a maximum output voltage variation of +/-10%. Double conversion mode is automatically restored as mains voltage varies beyond +/-10% with less than 1 millisecond transfer time between modes. | |
|--|--|--|
| High Availability UPS Features | Automatic inverter bypass; Manual bypass switch; Detachable hot-swap PDU; Hot swappable UPS power module; Hot swappable batteries | |
| Green Energy-Saving Features | High efficiency economy mode operation; Schedulable daily hours of economy mode operation | |
| CERTIFICATIONS | | |
| UPS Certifications | Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); CE; Meets FCC Part 15 Category A (EMI) | |
| UPS Certification Details | IEC 61000-4-5 1995 B Surge Immunity | |
| WARRANTY | | |
| Product Warranty Period (Worldwide) | 2-year limited warranty | |
| Connected Equipment Insurance (U.S., Canada & Puerto Rico) | \$250,000 Ultimate Lifetime Insurance | |

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.