

## SmartOnline 2.2kVA On-Line Double-Conversion UPS, 2U Rack/Tower, Interactive LCD display, 100/110/120/127V NEMA outlets

MODEL NUMBER: **SU2200RTXLCD2U**



### Description

Tripp Lite Smart Online UPS systems offer high performance power protection ideal for critical server and network equipment in datacenters, computer rooms and network closets. Online, double-conversion Uninterruptible Power Supply (UPS) maintains perfectly regulated output power by continuously converting raw AC input to DC, then re-converting output back to AC. Fully regulated sine wave AC output with +/-2% voltage regulation powers network equipment continuously, even during severe brownouts and overvoltages, all without depleting UPS battery reserves. Maintains battery-derived AC output during power failures with zero transfer time. Extended runtime options available. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Highly efficient operation in optional economy mode saves BTU heat output and energy costs. Network management interfaces support communications via USB, RS-232, contact-closure and optional SNMPWEBCARD network interface. Built-in DB9 port offers both enhanced RS-232 data and basic contact closure monitoring ability. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Includes PowerAlert monitoring software and complete cabling. Emergency Power Off (EPO) interface. LED display reports UPS operating mode, line power availability, battery mode operation, inverter operation, ECO mode status and output power availability. LED/LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode LCD configuration options. Programmable self-test. Fault-tolerant auto-bypass mode. Battery independent restart. Field-replaceable, hot-swappable internal batteries and external battery packs.

### Features

- Tripp Lite SU2200RTXLCD2U 2200VA / 2.2kVA / 1800W on-line, double-conversion 2U rack / tower UPS
- Selectable 100/110/120/127V output (120V factory preset)
- NEMA 5-20P input, 6 NEMA 5-15/20R and 1 L5-20R outlets
- Two switched 3-outlet load banks support remote reboot or programmable load shedding options
- Supports 2% output voltage regulation and zero transfer time in double conversion mode
- Economy mode option offers enhanced efficiency, reduced power consumption and lower BTU emissions

### Highlights

- 2200VA / 2.2kVA / 1800W on-line double-conversion 2U rack / tower UPS
- 100/110/120/127V 50/60Hz output; High efficiency economy mode option
- Interactive LCD with 9 selectable screens of UPS and site power data
- Expandable runtime, Hot-swap batteries, 19 in / 48.3cm depth
- USB, RS232 & EPO ports, support for SNMP/WEB card option
- 2 independently switched load banks
- NEMA 5-20P input; 6 NEMA 5-15/20R & 1 L5-20R outlets
- **This product is ENERGY STAR qualified for its ability to save customers money while helping to protect the environment**

### Package Includes

- SU2200RTXLCD2U UPS System
- PowerAlert Software with USB, Serial & EPO cabling
- 4 post rackmount installation kit
- Instruction manual



- 12 minutes runtime at 50% load (900W) and 4 minutes at 100% load (1800W) with internal batteries
- BP48V24-2U (limit 1), BP48V60RT-3U (multi-pack compatible) and BP48V27-2US (multi-pack compatible) external battery packs available (some configurations require Tripp Lite [External Battery Configuration Software](#))
- LCD interface reports operating mode plus 9 selectable screens of UPS data (Load % & kW, Load % & kVA, Power factor, Input volts & Hz, Output volts & Hz, Battery volts and charge %, Minutes runtime, Capacity remaining, Kw/hr. consumption)
- LCD interface also supports 16 screens of UPS configuration and setup options
- 4 post installation hardware included, Optional 2POSTRMKITWM enables 2 post rack installation, Optional 2-9USTAND enables tower placement
- Single line TEL / Network surge suppression
- Electronic bypass maintains utility output during a variety of UPS fault conditions
- Battery independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even when batteries are expired and require replacement
- Frequency regulation / conversion mode offers generator-compatible frequency correction or conversion of frequency from 50 to 60Hz or 60 to 50Hz
- USB, RS-232, contact-closure and optional SNMPWEBCARD accessory monitoring options
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Included PowerAlert UPS monitoring software

## Specifications

| OUTPUT  |  |
|---|--|
| Output Capacity Details                       | ON LINE MODE: Maximum output capacity ratings are reduced for some nominal voltage settings (127/120V 1800 watts / 115V 1620 watts / 110V 1530 watts / 100V 1440 watts). FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 1260 watts / 115V 1134 watts / 110V 1071 watts / 100V 1008 watts)  |
| Output Volt Amp Capacity (VA)                 | 2200   |
| Output kVA Capacity (kVA)                     | 2.2  |
| Output Watt Capacity (Watts)                  | 1800   |
| Output kW Capacity (kW)                       | 1.8  |
| Power Factor                                  | 0.82   |
| Crest Factor                                  | 3:1  |
| Nominal Output Voltage(s) Supported           | 100V; 110V; 115V; 120V; 127V   |
| Nominal Voltage Details                       | 120V factory-default nominal voltage   |
| Frequency Compatibility                       | 50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion  |
| Frequency Compatibility Details               | ON LINE MODE: Output frequency is automatically configured to match nominal input frequency on startup; Output matches input frequency when +/-5Hz of nominal; Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal. UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. FREQUENCY REGULATION / CONVERSION MODE: Output is regulated to +/-0.05Hz of selected output frequency input is 40 to 70Hz; UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. BATTERY MODE: Output is regulated to +/-0.05Hz. |
| Output Voltage Regulation (Line Mode)         | +/- 2%   |
| Output Voltage Regulation (Economy Line Mode) | +/- 10%  |



|  |   |
|--|---|
| Output Voltage Regulation (Battery Mode)   | +/- 3%  |
| UPS Output Receptacles                     | 6 5-15/20R outlet(s); 1 L5-20R outlet(s)  |
| Load Management Receptacles                | Two switchable three-outlet 5-15/20R load banks   |
| Output AC Waveform (AC Mode)               | Pure Sine wave  |
| Output AC Waveform (Battery Mode)          | Pure Sine wave  |
| <b>INPUT</b>                               |   |
| Rated input current (Maximum Load)         | 16A   |
| Nominal Input Voltage(s) Supported         | 100V AC; 110V AC; 115V AC; 120V AC; 127V AC   |
| Nominal Input Voltage Description          | 120V factory default  |
| UPS Input Connection Type                  | 5-20P   |
| Input Circuit Breakers                     | 30A   |
| UPS Input Cord Length (ft.)                | 10  |
| UPS Input Cord Length (m)                  | 3   |
| Recommended Electrical Service             | 20A 120V  |
| Input Phase                                | Single-Phase  |
| <b>BATTERY</b>                             |   |
| Full Load Runtime (min.)                   | 4 min. (1800w)  |
| Half Load Runtime (min.)                   | 12 min. (900w)  |
| Expandable Battery Runtime                 | Extended runtime supported via optional external battery packs  |
| External Battery Pack Compatibility        | <a href="#">BP48V24-2U</a> (limit 1); <a href="#">BP48V60RT-3U</a> (multi-pack compatible); <a href="#">BP48V27-2US</a> (multi-pack compatible) |
| Expandable Runtime Description             | Some external battery configurations require the use of Tripp Lite's External Battery Configuration Software, see manual for details            |
| DC System Voltage (VDC)                    | 48  |
| Battery Recharge Rate (Included Batteries) | Less than 3 hours recharge to 90% (typical, full load discharge)  |
| Internal UPS Replacement Battery Cartridge | <a href="#">RBC94-2U</a>  |
| Battery Access                             | Front panel battery access  |
| Battery Replacement Description            | Hot-swappable, user replaceable batteries   |
| <b>VOLTAGE REGULATION</b>                  |   |
| Voltage Regulation Description             | Online, double-conversion power conditioning maintains 2% output voltage regulation during brownouts and overvoltages                           |
| Overvoltage Correction                     | Corrects overvoltages to 150V (0-100% load)   |
| Undervoltage Correction                    | Corrects undervoltages to 100V at full load (90V at 100V nominal)   |



|   |   |
|---|---|
| Severe Undervoltage Correction                                | Corrects brownouts to 70V (70% load) & 55V (33% load)   |
| <b>LEDS ALARMS &amp; SWITCHES</b>                             |   |
| LED Indicators  | 7 front panel LEDs indicate line power availability, AC to DC conversion, battery mode operation, inverter mode, eco mode operation, bypass mode operation and AC output status   |
| Front Panel LCD Display                                       | Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options |
| Audible Alarm   | Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions   |
| Alarm Cancel Operation  | Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  |
| Switches  | 2 switches control off/on power status and alarm-cancel operation; 2 additional scroll-down and scroll-up / select options enable LCD status viewing and configuration options  |
| <b>SURGE / NOISE SUPPRESSION</b>                              |   |
| UPS AC Suppression Joule Rating                               | 570   |
| UPS AC Suppression Response Time                              | Instantaneous   |
| UPS Dataline Suppression                                      | 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet  |
| EMI / RFI AC Noise Suppression                                | Yes   |
| <b>PHYSICAL</b>   |   |
| Included Mounting Accessory Description                       | Includes 4 post rackmount installation accessories  |
| Installation Form Factors Supported with Optional Accessories | 2 post rackmount (2POSTRMKITWM); Tower (2-9USTAND); Wallmount (2POSTRMKITWM)  |
| Primary Form Factor   | Rackmount   |
| UPS Power Module Dimensions (hwd, in.)                        | 3.5 x 17.5 x 19   |
| UPS Power Module Dimensions (hwd, cm)                         | 8.9 x 44.4 x 48.3   |
| Rack Height   | 2U  |
| UPS Power Module Weight (lbs.)                                | 48.5  |
| UPS Power Module Weight (kg)                                  | 22  |
| UPS Shipping Dimensions (hwd / in.)                           | 9.5 x 20 x 24   |
| UPS Shipping Dimensions (hwd / cm)                            | 24.1 x 50.8 x 61  |
| Shipping Weight (lbs.)  | 61.5  |
| Shipping Weight (kg)  | 27.9  |
| Cooling Method  | Fan   |
| UPS Housing Material  | Steel   |



| <b>ENVIRONMENTAL</b>  |   |
|---|---|
| Operating Temperature Range                                 | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius   |
| Storage Temperature Range                                   | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  |
| Relative Humidity   | 0 to 95%, non-condensing  |
| AC Mode BTU / Hr. (Full Load)                               | 683   |
| AC Economy Mode BTU / Hr. (Full Load)                       | 390   |
| Battery Mode BTU / Hr. (Full Load)                          | 838   |
| AC Economy Mode Efficiency Rating (100% Load)               | 94%   |
| Operating Elevation (ft.)                                   | 0-3000m / 0-10,000 ft.  |
| Audible Noise   | 57 dBA at 1m front side   |
| Operating Elevation (m)                                     | 0-3000 m  |
| <b>COMMUNICATIONS</b>                                       |   |
| Communications Interface                                    | USB (HID enabled); DB9 Serial; Contact closure; EPO (emergency power off); Slot for SNMP/Web interface  |
| Network Monitoring Port Description                         | Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications                             |
| PowerAlert Software   | Included  |
| Communications Cable  | USB and DB9 cabling included  |
| WatchDog Compatibility                                      | Supports Watchdog application, OS and hard-reboot restart options for remote applications   |
| <b>LINE / BATTERY TRANSFER</b>                              |   |
| Transfer Time   | Zero (0 milliseconds) in double-conversion mode; 4 milliseconds economy mode  |
| Low Voltage Transfer to Battery Power (Setpoint)            | 100V at full load (90V full load at 100V nominal setting); 70V at 70% load; 55V at 33% load   |
| High Voltage Transfer to Battery Power (Setpoint)           | 150   |
| <b>SPECIAL FEATURES</b>                                     |   |
| Cold Start (Startup in Battery Mode During a Power Failure) | Cold-start operation supported  |
| High Availability UPS Features                              | Automatic inverter bypass; Hot swappable batteries  |
| Green Energy-Saving Features                                | High efficiency economy mode operation; Individually controllable load banks; Schedulable daily hours of economy mode operation                       |
| <b>CERTIFICATIONS</b>                                       |   |
| UPS Certifications  | Tested to UL1778 (USA); Tested to CSA (Canada); Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances); ENERGY STAR Qualified |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

| WARRANTY   |   |
|--|---|
| Product Warranty Period (Worldwide)                        | 2-year limited warranty                               |
| Connected Equipment Insurance (U.S., Canada & Puerto Rico) | \$250,000 <a href="#">Ultimate Lifetime Insurance</a> |

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.